
# deli

## LITHIUM-ION **ANGLE GRINDER**

DL-JM20-E1D4



### SPECIFICATIONS

Model	DL-JM20-E1D4		
Wheel diameter	100mm		
Spindle	M10		
Rated Speed	3500/6000/8500/min		
Net weight	2.0kg		
Rated voltage	20V		

General Power Tool Safety
Warnings

\$\Delta\$ Warnings and all safety warnings and all instructions. Failure to follow the warnings and instructions may result in electric shock, fire and/or serious injury.

7.

- Keep work area clean and well it. Cultered or dark areas with a control tools in explosive count and the control tools in explosive count of the control tools are control tools or explosive country of the country of the control tools of the country of the count

The costaide diameter and the thickness of your accessory must be within the capacity rating of accessory must be within the capacity rating of accessory must be within the capacity rating of accessory must be recorded to the capacity particles. Threaded mounting of accessors must match the grider spinel behalf of accessory must fit the locating diameter of the flagse. Accessors better that our furth the mounting humans of the power lost will not of or based accessory, better that the control particles are controlled to the control wheels for chips and cracks, backing on the power lost will not not do based to be the controlled to be the control wheels for chips and cracks, backing with the controlled to be the control was to be the controlled to the control was to be the controlled to the control was to be found in the diameter of the controlled to the control was to the controlled to the control was to the controlled to the control was to the control was to the controlled to the control was to the contr break apart during his test time.

Depending on application, use face sheld,
Mear personal protective equipment.

Depending on application, use face sheld,
Mear personal protective of the second control of the control of the control of the second control of the control of the

the least amount of wheel is exposed towards the operation. The gash related by product the goal related by product the goal related in the control of the c

27. For tools intended to be fitted with threaded hole wheel, ensure that the thread in the wheel is long enough to accept the spindle and the wheel is long enough to accept the spindle and the working of the property supported.

30. Check that the workpiece is property supported.

30. If operating time has become excessively shorter, stop operating immediately. It may result in a risk of overheating, possible burns and expension and the continues to a possible thread to be a possible to proper the continue of the spindle dust, use a short-circuit breaker (30 mA) to assure operator saidle, to be adjusted to proper spindle of the spindle of the

Symbols

no load speed

FOR BATTERY CARTRIDGE

1. Before using battery cartridge, read all instructions and cautionary markings on (1) battery charger, (2) battery, and (3) product using battery.

2. Do not disassemble battery cartridge.

disposal of battery.

SAVE THESE INSTRUCTIONS.

ACAUTION: Only use genuine batteries.
Use of non-genuine batteries, or batteries that have been altered, may result in the battery bursting causing fires, personal injury and damage, it will also void the warranty for the tool and charger.

surriely for more described in well also vice the surriely for more described in the first plant of the firs

charging it.

4. Charge the battery cartridge if you do not use it for a long period (more than six months).

规格	148x210mm	材质及要求	骑马钉; 封皮12	20g双胶纸,里线	纸80g双胶织	£
印刷颜色	■黑色				版本	1.0
备注	备注			文件编号	1	
批准	审核	校对	校验	制图艾聪	日期	

货号

DL-JM20-E1D4

货名

钾电角磨机

零件名称

说明书

### FUNCTIONAL DESCRIPTION

AUTION:
Always be sure that the tool is switched off and the battery cartridge is removed before adjusting or checking function on the tool.

talling or removing battery cartridge

always ch onesets









Tool / battery protection system

The tool is equipped with a toolbattery protection system. This system automatically cuts off power to the motor to extent tool and battery life.

The tool will automatically also during operation if the color of battery site placed under one of the following operation of the color battery is placed under one of the following Overload protection.



### ASSEMBLY

## Installing or removing wheel guard For tool with locking screw type wheel guard





AUTION:

Always be sure that the tool is switched off and the battery cartidge is removed before carrying out any version the battery cartidge is removed before carrying out any version the biot.

To sighten the lock nut, press the shall lock firmly so that the spirolle carrord revolve, then use the lock nut wench about so provided in descripting resolution. The same of security righter coclaimes.

The same of the same of

## OPERATION

- It should never be necessary to force the tool. The weight of the tool applies adequate pressure. Forcing and excessive pressure could cause dangerous wheel breakage. ALWAYS replace wheel if tool is dropped white
- grinding. NEVER bang or hit grinding disc or wheel onto



### MAINTENANCE





WARNING: Read all safety warnings and all instructions. Failure to follow the warnings and instructions may result in electric shock, fire or serious injury.

reference.
Used indoors to prevent rain. If the power cord is damaged, it must be replaced by the manufacturer, its maintenance department or a professional in order to avoid danger.



CHARGER OF EGILICATIONS					
Rated Input voltage	100-240V-50/60Hz				
Rated output voltage	20V				
Rated charging current	1.5A				
Rated power	31.5W				
Insulation grade	@/ <b>  </b>				
Weight	0.3kg				

Read instructions





Keep indoors to prevent rain

## 1. Battery charging

Awarning: charger and the battery pack are designed to match. Do not use other chargers to charge the battery or use this charger to charge other batteries. Do not connect any metal objects with the charger or battery. If the poles are in contact, it may cause a short circuit or electric shock.

Indicator status on/off/flash Indication

Green light flashes

# Under charging

Green light on Charging over Charging over Red light on Battery failure

Note: when the battery pack is removed from the charger or the battery pack is inserted into an un-powered charger, the battery pack will automatically discharge, so after long-term storage, it has to be recharged before use.

Battery Pack Self-repair
When a failed battery pack or a battery pack with very low
votings is inserted in the changer, the charger will first
detect and by to repair It. The process will take about 30 ammuniates (the green for flashede during the period). When
the repair is successful, at state format change. (The
control of the process of the period of the charge of the period of the perio

规格	148x210mm	材质及要求 骑马钉;封皮120g双胶纸,里纸80g双胶纸					
印刷颜色	版本 1.0				1.0		
备注						文件编号	1
批准	审 核	校 对	校验	制图は	<b></b>	日期	

货号

DL-JM20-E1D4

货名

锂电角磨机

零件名称

说明书

## Product Warranty Card

Dear users :

Thank you for buying our products. In order to ensure your profit, users who buy our products can contact local distributor or Specified repair stations with invoice and warranty cards if the product failures due to quality problems.

Warranty Notice:

1From (Ye

(Year/Month/Day) to \_

(Year/Month/Day), If the failure happen in normal use, our company will provide free warranty, parts replacement and other services according to the failure situation.

2. This warranty card and purchase invoice are the voucher of after-sales service provided by our company to customers. The card must be detailed only after filling in the following form and affixing the official seal with the distributor.

 $3.\mbox{ln}$  one of the following cases, free warranty service will be invalid, and maintenance fees will be required:

- (1) Exceed the expiration date;
- (2) Failure or damage caused by not following the requirements of the product manual, maintenance or improper storage;
- $\hbox{(3) Failure or damage caused by disassembling, repairing or modification of the product without the permission of our company}\\$
- (4) Machine breakdown or damage caused by force majeure;
- (5) Consumable accessories.

This card is issued with the product. One card for one machine, to ensure that you can fully enjoy the right to free warranty service provided by the company, please keep this card properly, lost will not be replaced.

Purchase	Date:	(Year/Month/Day)	١
Pulcilase	Date	 (Tear/Monthly Day)	ŧ.

**Product Certificate** 

Inspector:

01

Date of manufacture:

Reserved for future use

Version: 1.0 Date: May, 2021 NINGBO DELI TOOLS CO., LTD.

No. 128 Chezhan West Road, Huangtan Town, Ninghai County, Ningbo, Zhejiang, China info@nbdeli.com www.deliworld.com +86 574 87562689 MADE IN CHINA

规格	148x210mm	材质及要求 骑马钉;封皮120g双胶纸,里纸80g双胶纸				
印刷颜色	■黑色				版本	1.0
备注					文件编号	1
批准	审 核	校 对	校验	制图 艾聪	日期	